



| | |
|---------------------------------|---|
| Device short name | XW+ Power Distribution Panel |
| Product dimensions (H x W x D) | 76.1 x 40.6 x 21.0 cm (30.0 x 16.0 x 8.3 in) |
| Shipping dimensions (H x W x D) | 122.0 x 53.3 x 34.3 cm (48.0 x 21.0 x 13.5 in) |
| Shipping weight | 30.5 kg (67.2 lb) |
| Product number | 865-1015-01 |
| Included | XW+ PDP enclosure with a field-reversible panel door, includes wall mount bracket, and XW+ Conduit Box Three 60 A, 120/240 Vac, two-pole, Square-D, type QOU, DIN-rail mounted AC breakers for AC input, bypass and AC load (factory-installed), plus five AC breaker expansion positions One GJ 250A 160 Vdc, 3/8" stud DC breaker installed, plus two expansion positions Eight expansion positions for charge controller DC breakers One ground terminal bus bar, one neutral terminal bus bar and one battery negative terminal bus bar One pair #4/0 AWG Arctic Ultraflex Blue™ battery cables (factory installed and labeled, ready to connect) #6 AWG Arctic Ultraflex Blue™ AC wiring (factory installed and labeled, ready to connect) |
| Device short name | XW+ Power Distribution Panel (without AC breakers) |
| Product number | 865-1014-01 |
| Included | Same as XW+ PDP (865-1015-01), but does not include any AC breakers |
| Device short name | XW+ Installation Kit for INV 2 INV 3 PDP |
| Product dimensions (H x W x D) | 22.9 x 40.6 x 21.0 cm (8.5 x 16.0 x 8.3 in) |
| Shipping dimensions (H x W x D) | 44.5 x 33.3 x 30.5 cm (17.5 x 13.0 x 12.0 in) |
| Shipping weight | 10.5 kg (23.1 lb) |
| Product number | 865-1020-01 |
| Included | XW+ Conduit Box and AC Sync and Xanbus™ cables #6 AWG AC wiring to connect the inverter to the AC breakers One GJ 250A 160 Vdc, 3/8" stud DC breaker, one bus bar for DC positive and one pair #4/0 AWG battery cables |
| Device short name | XW+ Conduit Box |
| Product dimensions (H x W x D) | 22.9 x 40.6 x 21.0 cm (8.5 x 16.0 x 8.3 in) |
| Shipping dimensions (H x W x D) | 44.5 x 33.0 x 30.5 cm (17.5 x 13.0 x 12.0 in) |
| Shipping weight | 4.6 kg (10.0 lb) |
| Product number | 865-1025-01 |
| Included | XW+ Conduit Box |
| Device short name | Conext 120/240VAC Breaker Kit for Conext XW+ PDP |
| Usage | XW+ PDP for additional XW+ inverter chargers, single-phase/spit-phase |
| Product number | 865-1215-01 |
| Included | Three 60 A, 120/240 Vac, two-pole, Square-D, type QOU, DIN-rail mountable AC breakers, jumpers, bypass interlock |
| Device short name | Conext three-phase Breaker Kit for Conext XW+ PDP |
| Usage | XW+ PDP for additional XW+ inverter chargers, three-phase |
| Product number | 865-1315-01 |
| Included | Three 60 A, 120/208 Vac, three-pole, Square-D, type QOU, DIN-rail mountable AC breakers, jumpers, bypass interlock |
| Device short name | 100A, 125VDC Breaker Master Pack (12 units) |
| Usage | XW+ PDP for MPPT 80 600 output, battery side |
| Product number | 865-1080 |
| Device short name | 80A, 125VDC Breaker Master Pack (12 units) |
| Usage | XW+ PDP for MPPT 60 150 output, battery side |
| Product number | 865-1070 |
| Device short name | 60A, 160VDC Breaker Master Pack (48 units) |
| Usage | XW+ PDP for MPPT 60 150 input, PV array side |
| Product number | 865-1075 |
| Device short name | 250A, 160VDC Breaker Master Pack (6 units) |
| Usage | XW+ PDP for inverter charger connection to battery |
| Product number | 865-1065 |

Specifications are subject to change without notice.


Conext XW+ Power Distribution Panel and accessories work with the following Schneider Electric products



Conext XW+ inverter/charger
XW+ 5548 NA Product no. 865-5548-01
XW+ 6848 NA Product no. 865-6848-01
XW+ 7048 E Product no. 865-7048-61
XW+ 8548 E Product no. 865-8548-61



Conext MPPT 60 150 solar charge controller
Product no. 865-1030-1



Conext MPPT 80 600 solar charge controller
Product no. 865-1032