Power Optimizer

For North America

P320 / P340 / P370 / P400 / P405 / P505





POWER OPTIMIZER

PV power optimization at the module-level

- Specifically designed to work with SolarEdge inverters
- Up to 25% more energy
- Superior efficiency (99.5%)
- Mitigates all types of module mismatch losses, from manufacturing tolerance to partial shading
- Flexible system design for maximum space utilization

- Fast installation with a single bolt
- Next generation maintenance with modulelevel monitoring
- Meets NEC requirements for arc fault protection (AFCI) and Photovoltaic Rapid Shutdown System (PVRSS)
- Module-level voltage shutdown for installer and firefighter safety



/ Power Optimizer **For North America**

P320 / P340 / P370 / P400 / P405 / P505

Optimizer model (typical module compatibility)	P320 (for 60-cell modules)	P340 (for high- power 60-cell modules)	P370 (for higher- power 60 and 72-cell modules)	P400 (for 72 & 96- cell modules)	P405 (for thin film modules)	P505 (for higher current modules)			
INPUT				,	•		•		
Rated Input DC Power ⁽¹⁾	320	340	370	400	405	505	W		
Absolute Maximum Input Voltage (Voc at lowest temperature)	2	48	60	80	125(2)	83(2)	Vdc		
MPPT Operating Range	8 - 48		8 - 60	8 - 80	12.5 - 105	12.5 - 83	Vdc		
Maximum Short Circuit Current (Isc)		11		10.1 14			Adc		
Maximum DC Input Current	13.75			12.63 17.5			Adc		
Maximum Efficiency	99.5								
Weighted Efficiency	98.8 98.6						%		
Overvoltage Category				II					
OUTPUT DURING OPER	RATION (POWE	R OPTIMIZER C	ONNECTED TO	OPERATING SO	LAREDGE INVE	RTER)			
Maximum Output Current	15								
Maximum Output Voltage	60 85								
INVERTER OFF) Safety Output Voltage per Power Optimizer	DBY (POWER OPTIMIZER DISCONNECTED FROM SOLAREDGE INVERTER OR SOLAREDGE 1 ± 0.1								
STANDARD COMPLIAN	ICE								
EMC		FC	CC Part15 Class B. IEC6	51000-6-2, IEC61000-6	5-3				
Safety	FCC Part15 Class B, IEC61000-6-2, IEC61000-6-3 IEC62109-1 (class II safety), UL1741								
RoHS	Yes								
INSTALLATION SPECIFI	CATIONS								
Maximum Allowed System Voltage	1000								
Compatible inverters	All SolarEdge Single Phase and Three Phase inverters								
Dimensions (W x L x H)	129	x 153 x 27.5 / 5.1 x 6		129 x 153 x 33.5 / 5.1 x 6 x 1.3	129 x 159 x 49.5 / 5.1 x 6.3 x 1.9	129 x 162 x 59 / 5.1 x 6.4 x 2.3	mm / in		
Weight (including cables)	630 / 1.4			750 / 1.7	845 / 1.9	1064 / 2.3	gr / lb		
Input Connector	MC4 ⁽³⁾								
Output Wire Type / Connector	Double Insulated; MC4								
Output Wire Length	0.9 / 2.95						m / ft		
Input Wire Length	0.16 / 0.52								
Operating Temperature Range	-40 - +85 / -40 - +185								
Protection Rating	IP68 / NEMA6P								
Relative Humidity	0 - 100								

⁽¹⁾ Rated STC power of the module. Module of up to +5% power tolerance allowed (2) NEC 2017 requires max input voltage be not more than 80V (3) For other connector types please contact SolarEdge

PV System Design Using a SolarEdge Inverter ⁽⁴⁾⁽⁵⁾		Single Phase HD-Wave	Single phase	Three Phase 208V	Three Phase 480V		
Minimum String Length	P320, P340, P370, P400	8		10	18		
(Power Optimizers)	P405 / P505	6		8	14		
Maximum String Length (Power Optimizers)		25		25	50(6)		
Maximum Power per String		5700 (6000 with SE7600-US - SE11400- US)	5250	6000 ⁽⁷⁾	12750 ⁽⁸⁾	W	
Parallel Strings of Different Lengths or Orientations		Yes					

⁽a) For detailed string sizing information refer to: http://www.solaredge.com/sites/default/files/string_sizing_na.pdf
(b) It is not allowed to mix P405/P505 with P320/P340/P370/P400 in one string
(a) A string with more than 30 optimizers does not meet NEC rapid shutdown requirements; safety voltage will be above the 30V requirement
(b) For SE14.4KUS/SE43.2KUS: It is allowed to install up to 6,500W per string when 3 strings are connected to the inverter (3 strings per unit for SE43.2KUS) and when the maximum power difference between the strings is up to 1,000W
(a) For SE30KUS/SE33.3KUS/SE66.6KUS/SE100KUS: It is allowed to install up to 15,000W per string when 3 strings are connected to the inverter (3 strings per unit for SE66.6KUS/SE100KUS) and when the maximum power difference between the strings is up to 1,000W and when the maximum power difference between the strings is up to 2,000W